



# Tuner Box S2

## Micro-sized FM-Tuner

- Micro-sized FM-Tuner
- 99 presets
- Manual or automatic tuning
- Adaptive noise reduction
- High-contrast dot-matrix display
- Display of frequency, preset number, centre of station, Stereo or Mono reception, signal strength
- Trigger switching (on/off)
- Full function IR remote control
- Aluminium case in new S2 design
- Available in silver or black

colour options: ● ●

<b>Tuning range FM-band:</b>	87,5 - 108MHz (50kHz steps)
<b>Programmable presets:</b>	99
<b>Frequency response:</b>	20Hz - 20kHz ( $\pm 1$ dB)
<b>S/N ratio:</b>	50dB
<b>THD:</b>	0,05% / $\Delta f$ 75kHz and f mod 1kHz
<b>Stereo separation:</b>	30dB / $\Delta f$ 75kHz and f mod 1kHz
<b>Sensitivity:</b>	7dB / $\mu$ V mono, 17dB / $\mu$ V stereo /75 ohms
<b>Antenna input:</b>	1 x co-axial DIN-socket (75 ohms) / US-model F-socket
<b>Line-level output:</b>	1 pair RCA/phono sockets
<b>Trigger in and out:</b>	2-pole coaxial 2,5mm jack
<b>Output voltage:</b>	0,775Vrms
<b>Outboard power supply:</b>	5V/1A DC; 110-240V/50, 60Hz
<b>Power consumption:</b>	70mA DC, <1W in standby
<b>Dimensions W x H x D:</b>	103 x 37 x 112 (121) mm
<b>Weight:</b>	315g without power supply